
Connection Diagram for AC/Brushless Servomotors with Euro Connectors and Incremental Optical **Encoder / Commutation**



SUPPLY CONNECTOR (OPTION)


FUNCTION
MOTOR U
MOTOR V
BRAKE B+ (If fitted)
BRAKE B- (if fitted)
MOTOR W
MOTOR EARTH 🕹



INTERCONNECTRON SIZE 1 6 PIN

FEEDBACK CONNECTOR

PIN FUNCTION	COLOUR
1 A CHANNEL (ENC 2)	BLU
2 A CHANNEL (NOT ENC 2)	BLU/BLK
3 Z CHANNEL (ENC O)	YEL
4 V CHANNEL (POS SIG A)	GRY/BLK
5 U CHANNEL (POS SIG NOT C)	BRN
6 U CHANNEL (POS SIG C)	BRN/BLK
7 GROUND	BLK
8 THERMAL SENSOR	1
9 THERMAL SENSOR	1
10 +5V DC	RED
11 B CHANNEL (ENC 1)	GRN
12 B CHANNEL (NOT ENC 1)	GRN/BLK
13 Z CHANNEL (NOT ENC O)	YEL/BLK
14 V CHANNEL (POS SIG NÓT A)	GŔY
15 W CHANNEL (POS SIG NOT B)	WHT/BLK
16 W CHANNEL (POS SIG B)	WHT
[17]	



CONNECTORS VIEWED FROM CUSTOMER SIDE.